



**INSTRUCTION MANUAL**

**BICONICAL**

**ANTENNA**

**MODEL BIA-30S**

**20 MHz – 300 MHz**

# INSTRUCTION MANUAL

**THIS INSTRUCTION MANUAL AND ITS  
ASSOCIATED INFORMATION IS  
PROPRIETARY. UNAUTHORIZED  
REPRODUCTION IS FORBIDDEN.**

**© 1996 ELECTRO-METRICS CORP.**

## **BICONICAL ANTENNA**

**20 MHz – 300 MHz**

**ELECTRO-METRICS**

**MODEL BIA-30S**

**SERIAL NO: N/A**

## **ELECTRO-METRICS CORPORATION**

**231 Enterprise Road, Johnstown, New York 12095**  
**Phone: (518) 762-2600      Fax: (518) 762-2812**

**EMAIL: [info@emihq.com](mailto:info@emihq.com)**

**WEB: <http://www.electro-metrics.com>**

**MANUAL REV. NO: BIA30HF-0196**

**ISSUE DATE: JANUARY 01 1996**

# **WARRANTY**

**This Model BIA-30S Biconical Antenna is warranted for a period of 12 months (USA only) from date of shipment against defective materials and workmanship. This warranty is limited to the repair of or replacement of defective parts and is void if unauthorized repair or modification is attempted. Repairs for damage due to misuse or abnormal operating conditions will be performed at the factory and will be billed at our commercial hourly rates. Our estimate will be provided before the work is started.**

**DESCRIPTION AND USE ELECTRO-METRICS  
MODEL EM-6912 BICONICAL ANTENNA**

## **1.0 Description**

The EM-6912 Biconical Antenna performs E-field measurements from 20 MHz to 300 MHz in accordance with FCC Part 15 and 18, VDE 0871 and 0875, MIL-STD-461 Method RE02, plus other commercial, military, and government EMI specifications.

The biconical elements are made from aluminum rods, joined to the end pieces by tack welds. In addition, each element cage has a cross piece connecting the center element to an outer element. The elements mount in a balun network, fabricated from phenolic, containing the necessary impedance-matching components.

Each series of antennas is calibrated during manufacturing, with the calibration data (at 1 and 3 meters) included in the manual as gain and antenna factors vs frequency for use in Specification Compliance Testing. For the maximum power handling capability of the EM-6912, refer to Table 1.

The balun, feedline, and element cage design contribute to producing a response curve that is almost linear. This makes the antenna ideal for vertical and horizontal swept site attenuation measurements per ANSI and FCC specifications.

A 20 dB preamplifier is recommended in-line with the receiving antenna to minimize the required transmitted power and reduce the possibility of saturation of the transmitting antenna.

When the EM-6912 is oriented vertically, the same element orientation need not be maintained from measurement to measurement. This insensitivity to orientation in the vertical plane is a result of the balun and other design features.

## **2.0 Specifications**

### **2.1 Electrical**

Frequency Range:	20-300 MHz
Input Impedance:	Matched to 50Ω.
VSWR:	Average: 1.4:1 with 6 dB pad. Maximum: 1.8:1 with 6 dB pad.
Max. Continuous Power:	0.5 W.

Peak Power: 1.0 W.  
 Connector: BNC, female.

## 2.2 Mechanical

Length: 1320 mm (52") tip-to-tip.  
 Diameter: 508 mm (20") maximum.  
 Depth: 560 mm (22") including balun.  
 Weight: 2.7 kg (6 lbs).

TABLE 1

TYPICAL POWER HANDLING BEFORE SATURATION

ELECTRO-METRICS MODEL EM-6912 BICONICAL ANTENNA

FREQUENCY (MHz)	POWER (MAX.) (mW)	FREQUENCY (MHz)	POWER (MAX.) (mW)
30	82.4	110	4.72
35	108.8	115	6.32
40	66.9	120	4.93
45	107.4	125	4.89
50	82.8	130	3.40
55	85.8	135	3.79
60	93.3	140	1.02
65	42.0	145	0.7147
70	31.6	150	0.5071
75	26.5	155	0.4735
80	16.9	160	0.4286
85	7.63	200	0.4297
90	10.2	220	0.4282
95	8.92	270	0.4276
100	5.64	300	0.4297
105	7.89		

GAIN AND ANTENNA FACTORS

FOR

MODEL EM-6912

BICONICAL ANTENNA

AT

1 METER, 3 METER

1 METER: PAGE 4

3 METER: PAGE 5

ELECTRO-METRICS  
GAIN AND ANTENNA FACTORS  
MODEL EM-6912  
BICONICAL ANTENNA  
1 METER CALIBRATION  
PAGE 4A

ELECTRO-METRICS  
GAIN AND ANTENNA FACTORS  
MODEL EM-6912  
BICONICAL ANTENNA  
3 METER CALIBRATION  
PAGE 5A